




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04B 1/40	A1	(11) International Publication Number: WO 99/62194 (43) International Publication Date: 2 December 1999 (02.12.99)
<p>(21) International Application Number: PCT/US99/11734</p> <p>(22) International Filing Date: 27 May 1999 (27.05.99)</p> <p>(30) Priority Data: 09/086,804 29 May 1998 (29.05.98) US</p> <p>(71) Applicant (for all designated States except US): MOTOROLA, INC. [US/US]; 1303 East Algonquin Road, Schaumburg, IL 60196 (US).</p> <p>(72) Inventor; and (75) Inventor/Applicant (for US only): PALERMO, Keith, Charles [US/US]; 326 W. Brisa Drive, Gilbert, AZ 85233 (US).</p> <p>(74) Agents: INGRASSIA, Vincent, B. et al.; Motorola, Inc., Intellectual Property Dept., P.O. Box 10219, Scottsdale, AZ 85271-0219 (US).</p>		<p>(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, US, UZ, VN, YU, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SL, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).</p> <p>Published With international search report.</p>

(54) Title: MULTIPLE WAVEFORM SOFTWARE RADIO



(57) Abstract

A radio is disclosed in which different waveforms may be utilized. The radio includes a memory (801) in which software (802, 805, 806) for specific waveforms is stored. The radio further includes one or more processors (807, 809, 811) which extract waveform specific software to process information for transmission or reception. All processing of the information between reception or reproduction of speech and transmission and reception of radio frequency signals, respectively, is performed in software.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

MULTIPLE WAVEFORM SOFTWARE RADIO

FIELD OF THE INVENTION

5 This invention pertains to radio transmitters and receivers.

BACKGROUND OF THE INVENTION

Commercial and military radios often need to communicate or could benefit by
10 having the capability of communicating with two or more radio networks, each of
 which is of a different type. One example of this need is found in the cellular
 telephone market where different modes of operation are presently available leading
 to the present need for so-called "dual mode" cellular phones. The dual modes refer
 to different waveforms. As used herein, "waveform" refers to functional
15 transformation of information such as speech to a modulated rf carrier and
 encompasses the entire process of going from speech to antenna and/or vice versa.
 To operate over multiple waveforms has in the past required that various pieces of
 equipment be utilized. As new waveform technologies develop, existing equipment
 becomes unusable with such waveforms.
20 It is desirable to provide a radio which is useable as a generic radio platform with
 existing waveforms and yet to be developed waveforms.

BRIEF DESCRIPTION OF THE DRAWING

25 The invention will be better understood from a reading of the following detailed
 description in conjunction with the drawing in which like reference designators
 indicate like elements in the various drawing figures, and in which:

 Fig. 1 is a functional diagram of a radio transmit path in accordance with the
 invention;

30 Fig. 2 is a partial block diagram of the transmit path of Fig. 1;

Fig. 3 is a functional diagram of a radio receive path in accordance with the invention;

Fig. 4 is a partial block diagram of the receive path of Fig. 3;

Fig. 5 is block diagram of a transmit path of a second radio in accordance with
5 the invention;

Fig. 6 is a block diagram of a receive path of a second radio in accordance with the invention;

Fig. 7 illustrates the tasks performed by one of the transmit path processors of Fig. 5;

10 Fig. 8 is a block diagram of waveform software loading utilized in the second radio of Figs. 5 and 6;

Fig. 9 is a flow diagram illustrating the setup process of a radio in accordance with the invention;

15 Fig. 10 is a diagram of the broadband rf receive circuit utilized in a radio in accordance with the invention; and

Fig. 11 is a diagram of the broadband rf up converter circuit utilized in a radio in accordance with the invention.

DETAILED DESCRIPTION

20

The invention is directed to a software radio in which operation is, for the most part, effected by a software program that runs on a generic radio platform.

Interoperable waveform modes are added as software applications in a manner similar to adding applications to a personal computer. In accordance with one aspect
25 of the invention, the radio user or operator selects stored waveforms on demand as communications requirement dictate. As is described below, one embodiment of the invention utilizes nonvolatile storage to implement a plurality of waveforms. The operator may place one or more of the waveforms in cache random access memory such that rapid switching between the selected waveforms can occur. In addition, the
30 operator may switch from one waveform mode to another to communicate over different radio networks, such as the Iridium satellite communication network

manufactured by Motorola, Inc., TDMA and/or CDMA cellular networks, or other land mobile two-way radio systems such as the IDEN system by Motorola, Inc., or can broadcast on all or a number of them simultaneously.

Turning now to FIG. 1, a functional flow diagram of a transmitter in accordance with the invention is shown. In the arrangement of Fig. 1, speech is applied to a voice conditioning function 101 that includes speech compression. In some instances, the waveform to be generated may not require compression in which event the speech compression portion of function 101 is not utilized. The conditioned and possibly compressed speech is subjected to an encryption function 103. The encrypted speech is provided to a modulation function 105. The modulation function provides any of a plurality of modulation types. The types of modulation which may be utilized includes frequency modulation (fm), amplitude modulation (am), frequency shift keying (fsk), phase shift keyed, (psk), quadrature amplitude modulation (qam), time division multiplexing (tdma), code division multiplexing (cdma) and other modulation functions. The various modulation types identified above are known, as are specifics with respect to the functionality of these and other modulation types. The modulation may be analog in nature or it may be digital. The modulation output is fed to a radio frequency (rf) up-conversion function 107. Function 107 utilizes the baseband modulation output of modulation function 105 and converts the baseband modulation to an rf carrier. Function 107 provides for selectable rf up-conversion and the resulting modulated rf carrier is applied to antenna 109. Although one antenna is shown, antenna 109 may include one or more antennas each of which is operable over one or more specific frequency bands.

Fig. 2 illustrates in block diagram form an implementation of the transmitter of Fig. 1. Speech is applied to an analog to digital converter or digitizer 201 to produce digital information. All processing of the digital information is performed in software. The output of digitizer 201 is a digital data stream that enters one or more microprocessor blocks shown illustratively as processors 203. Any number of separate processors may be disposed between the two processors 203 shown to perform the various functions shown in the functional diagram of Fig. 1 such as voice conditioning and compression functions 101, encryption functions 103 and

modulation functions 105. The output of the final or nth processor 203 is applied to a digital to an analog conversion block comprising digital to analog converters 207, 208. Each of digital to analog converters 207, 208 generates a baseband representation of the modulated signal in phase and quadrature components I and Q, respectively. I and Q are applied to respective mixers 209, 211. Mixers 209, 211 receive cosine and sine carrier signals generated by an rf synthesizer 213. The outputs of mixers 209, 211 are combined in adder 215 to produce a modulated rf signal which is applied to a power amplifier 217 to amplify the output signal to a desired level. The rf output of power amplifier 217 is applied to antenna 109.

In the transmitter of Fig. 2, each of processors 203 is utilized to provide a portion of the processing power needed to implement any desired waveform so that changing a waveform changes the software that processors 203 execute. Although multiple processors are shown, it will be understood by those skilled in the art that multiple processors, each specific to a waveform may be utilized in some embodiments of the invention. In other embodiments of the invention, multitasking of a fewer number of processors can accomplish the same result. In yet other embodiments of the invention, certain processors may be provided which are dedicated to the production of certain waveforms and other processors may be multitasked. In one implementation of the invention, the structure of Fig. 2 is replicated for each rf channel. The specific embodiment of Fig. 2 can operate to produce any one of several waveforms on a single rf channel. To accommodate additional channels the circuit of FIG. 2 may be replicated.

The analog to digital converters 201 are of conventional design and are of a type that is commercially available. Similarly, the processors 203 are commercially available processors such as the MPC860 available from Motorola, Inc. The rf up-converter 107 can be one of several commercially available rf up-converters.

Commercial transceivers include both transmit portions and receive portions. A receiver in accordance with the invention is shown in a functional diagram in Fig. 3. Signals are received at antenna 301 which may be the same physical antenna as antenna 109 as shown in Figs. 1 and 2 or may be a separate receive antenna. Alternatively, a common antenna may be used and conventional techniques and

apparatus may be used to provide isolation between transmit and receive portions of a transceiver in accordance with the invention.

Signals are received by antenna 301 and down converted to baseband signals by rf down converter 303. A demodulation function 305 demodulates the baseband
5 signals using any one of a plurality of modulation formats such as the various modulation formats described in conjunction with the modulation function 105 shown in Fig. 1. The modulation format utilized depends upon the particular modulation format employed by the particular waveform that is received. The demodulation function 305 outputs a demodulated data stream to decryption function 307 that
10 performs the decryption, if any, required. The output of decryption function 307 is provided to voice decompression function 309 that decompresses the speech signals and provides a decompressed speech output. The functional diagram of Fig. 3 is for a single channel.

Fig. 4 illustrates the receiver of Fig. 3 in block diagram form. RF signals are
15 received at antenna 301 and may be amplified by a low noise amplifier (Ina) 401 which is of conventional design, but ideally is of a broadband design. The output of Ina 401 is applied to an rf down converter 303 which includes an rf down converter 411 of conventional design which for example generates phase and quadrature signals I and Q. The outputs I and Q are applied to analog to digital converters 407,
20 409 which are of conventional design. The I and Q outputs are applied to processors 403. The processors 403 provide the functions of demodulation 305, decryption 307 and voice decompression 309. Just as the processors 203 of Fig. 2 may be implemented as one or more processors, the processors 403 may similarly be one or more processors. The output of the processors 403 is a digital data stream that
25 digital to analog converter 405 converts to analog speech signals. Multiple waveforms may be accomplished by executing different software routines in processors 403. The processors 403 may in a transceiver be included in processors 203.

Fig. 5 illustrates an arrangement for the simultaneous transmission of a
30 plurality of waveforms. In the arrangement shown four waveforms may be simultaneously transmitted over four rf channels. Those skilled in the art will

appreciate that any number of waveforms may be simultaneously generated and transmitted by varying the number of channel paths from the four shown. The four rf channels are each similar to the single channel transmitter path of Fig. 1. Each of the four channels has a corresponding speech or data input, speech1, speech2, speech3
5 and data. The speech inputs are coupled to analog to digital converters 501, 503, 505, respectively. The outputs of the analog to digital converters 501, 503, 505 are applied to a processor arrangement comprising processors 507, 515, 523. Processor 507 includes vocoder functionality to provide voice compression and other vocoder functionality. Processor 515 provides encryption functionality and processor 523
10 provides modulation functionality. The outputs of processor 523 feed digital to analog converters 531, 533; and 535, 537; and 539, 541 that in turn provide base band quadrature signals to respective up converters 543, 545, 547 that are respectively connected to antennas 549, 551, 553. The speech inputs to the various channels may be derived from the same source such as a microphone or can come
15 from a different source. The functions provided by processors 507, 515, 523 are implemented in software so that they can be selected dynamically, changed dynamically and the parameters of those functions are changeable dynamically. For example, the modulation bit rate and the modulation bandwidth are changeable dynamically. A user interface 561 is provided to permit the user of the transmitter to
20 indicate, for example, that the user desires to communicate over a police VHF channel. The user interface is coupled to one or more control functions 563, 565, 567 which are in turn coupled functionally to the processors 507, 515, 523. The control functions 563, 565, 567 in turn control the operations of vocoder functions 509, 511, 513 encryptor functions 517, 519, 521 and modulation functions 525, 527,
25 529 respectively. In addition the control function 567 controls the operation of the rf up-converters 543, 545, 547.

The transmitter may also be used for the transmission of data over an rf channel. Data input is initially applied to a data interface 571 that is in turn coupled to functionalities in processors 507, 515, 523. Processor 507 includes a protocol
30 stack 572 that provides various protocol conversions such a TCPIP for Ethernet conversions. Processor 515 includes encryption functionality 573 to encrypt the

protocol-converted data from processor 507. The output of processor 515 is in turn coupled to modulation functionality 575 of processor 523. Digital to analog converters 577, 579 provide in phase and quadrature signals to an rf up-converter 581 which transmits over antenna 583.

5 Fig. 6 illustrates a multi-channel receiver in accordance with the invention for the simultaneous reception of a plurality of waveforms. In the arrangement shown four waveforms that may be simultaneously received over four rf channels. Those skilled in the art will appreciate that any number of waveforms may be simultaneously received and processed by varying the number of channel paths from the four shown.

10 The four rf channels are each similar to the single channel transceiver path of Fig. 3. RF signals for the speech channels are received over the antennas 649, 651, 653. RF down-converters 643, 645, 647, respectively. The outputs of the down converters 643, 645, 647 are respectively applied to analog to digital converter pairs 631, 633; 635, 637; 639, 641. The outputs of the digital to analog converter pairs are provided

15 to processors 623, 615, 607 that provide demodulation functions 625, 627, 629; decryption functions 617, 619, 621 and vocoder functionality 609, 611, 613. The digital outputs of processor 607 are converted into speech signals by digital to analog converters 601, 603, 605. A user interface 661 is used to provide control information relative to control function 663, 665, 667 of processors 607, 615, 623 whereby

20 waveform software is selected.

 The receiver of Fig. 6 may also process data signals. Data signals are received over antenna 681 and provided to rf down converter 682. Down converter 682 is coupled to analog to digital converter pair 683, 685. The output of digital to analog converter pair 683, 685 is coupled to demodulator function 687, decryption

25 function 689 and a protocol stack 691. The output of the protocol stack 691 is a received digital data output.

 Fig. 7 illustrates the multi-tasking of a processor such as processor 607. Processor 607 multi-tasks all functions assigned to it for all the channels that are in operation. As illustrated, processor 607 performs the vocoder operations 701 for

30 vocoder 1 at a time $t(k)$ followed sequentially by vocoder operation 702 for vocoder 2 and then vocoder operations 703 for vocoder 3. The sequence repeats for as long as

all three vocoder functions are required. In the event that fewer than three or more than three vocoder functions are to be utilized, the number and sequence of functions processed changes. In addition, processor 607 may perform other functions and those functions would be likewise inserted into the timeline shown.

5 Fig. 8 illustrates an arrangement for use with processors which permits the rapid switching of waveform functionality. In accordance with an embodiment of the invention, the functionality of a processor is obtained from a collection of waveform software accessible to each processor. As shown in Fig. 8 three processors 807, 809, 811 each have associated therewith cache memory 813, 815, 817 respectively.

10 A memory 801 accessible to each of processors 807, 809, 811 contains waveform software 803, 805, 806 for the various waveforms that may be processed. The memory 801 is for example a disk drive. To permit the rapid switching between waveforms, high-speed memory such as ram or random access memory is used for the caches 813, 815, 817. In operation, if a user of the system utilizing the

15 processors selects a waveform to be utilized, the system processors 807, 809, 811 retrieve the appropriate waveform software from hard disk memory 801 and causes the appropriate software to be stored in the cache memories 813, 815, 817. Thus, for example, if waveform 1 is selected, waveform 1 vocoder software 819 is retrieved from memory 801 and stored in cache 813; waveform 1 encryption software 821 is

20 retrieved from memory 801 and stored in cache 815; and waveform 1 modulator software 823 is retrieved from memory 801 and stored in cache 817. Similarly, software for other waveforms is retrieved from memory 801 and stored in caches 813, 815, 817 for other selected waveforms. Thus in accordance with one aspect of the invention, all of the constituent parts of a wave form application function are

25 distributed to the processors that need to execute them. As shown in Fig. 8, no designation is made as to whether the system is operating as receiver or as transmitter. The operation of the system of Fig. 8 is the same whether operating as receiver, transmitter or transceiver. Operation of the system structure of Fig. 8 is shown in Fig. 9. In step 901, the user selects the waveform or waveforms that are to

30 be used. In response to such selection, the system retrieves the waveform application routines from memory 801 as indicated at step 903. The waveform

applications are stored in the cache memories 813, 815, 817 for the processors 807, 809, 811 as indicated at step 905. In step 905, the waveform application is disseminated to each processor cache as necessary to process the related waveform. At step 907, waveform programmable information such as bandwidth, sample rates and frequencies of operation are provided.

In operation of the system one or more of the waveform software is stored in dedicated memory which is rapidly accessed at power up of the radio. By adding flash memory 841, 843, 845 to each of the processors 807, 809, 811 respectively, the last number of waveforms used by the radio user prior to power down are stored in memory 841, 843, 845 and are instantly loaded at next power up. This permits the software radio to power up for substantially instantaneous use.

Fig. 10 illustrates in block diagram form the rf receive function to support multiple waveforms. Signals are received at antenna 1017 and applied to Ina 1015. The output of Ina 1015 is applied to mixers 1009, 1011. Each mixer 1009, 1011 also has sine and cosine inputs, respectively from a programmable adjustable frequency synthesizer 1013. To support waveforms that may be at different frequency ranges, synthesizer 1013 has a broadband frequency range. The outputs of mixers 1009, 1011 are applied to adjustable low pass filters 1005, 1007. The outputs of low pass filters 1005, 1007 are applied to analog to digital converters 1001, 1003. The analog to digital converters 1001, 1003 utilize numerically controlled oscillator 1019 to determine the appropriate sampling rate for the waveform. In addition, the arrangement of Fig. 10 includes an adjustable automatic gain control circuit or function 1004. The various waveforms that may be processed have different acquisition and agc requirements. Accordingly, it is necessary that the agc parameters, such as loop bandwidth, and track and hold characteristics, are adjustable.

Fig. 11 illustrates in block diagram form the rf transmit function. Baseband quadrature signals I, Q are applied to digital to analog converters 1101, 1103 that are clocked by the numerically controlled oscillator (nco) 1105. The analog outputs are applied to programmable adjustable filters 1107, 1109. Filters 1107, 1109 are utilized to control spectral content of the output signal. Outputs of filters 1107, 1109 are fed

to mixers 1111, 1113 that also receive inputs from a quadrature synthesizer 1115. To support waveforms that may be at different frequency ranges, synthesizer 1115 has a broadband frequency range. The outputs of mixers 1111, 1113 are in turn fed to summer 1117 that is coupled to power amplifier 1119. Power amplifier 1119 is
5 adjustable such that the power output may be varied. Power amplifier 1119 is in turn coupled to antenna 1121.

The invention has been described in terms of various embodiments. It will be understood by those skilled in the art that various changes and modifications may be made to the embodiments without departing from the spirit or scope of the invention.
10 It is not intended that the invention be limited in any way to the embodiments shown and described herein and it is intended that the invention be limited only by the claims appended hereto.

WHAT IS CLAIMED IS:

1. A radio transmitter comprising:
 - an information receiving input receiving input digital information;
 - 5 an rf up-converter operable over a plurality of waveforms; and
 - one or more processors disposed between said input and said rf up-converter and operable in accordance with a plurality of predetermined waveform software each waveform software being associated with a corresponding one of a plurality of waveforms such that said digital information is processed in accordance with
 - 10 selected ones of said plurality of predetermined waveform software to produce digital output information representative of said input digital information for said rf up converter whereby one or more waveforms of said plurality of waveforms is produced.
- 15 2. A radio transmitter in accordance with claim 1, comprising:
 - a first memory having stored therein said plurality of predetermined waveform software;
 - a second memory for receiving one or more waveform software of said plurality of waveform software for a corresponding number of selected ones of said
 - 20 plurality of waveforms, said second memory receiving said one or more waveform software from said first memory; and
 - said second memory being coupled to said one or more processors to provide said selected ones of said predetermined waveform software to said one or more processors.
- 25 3. A radio transmitter in accordance with claim 2, comprising:
 - a user interface operable to select said one or more of said plurality of predetermined waveforms.
- 30 4. A radio transmitter in accordance with claim 3, wherein:

said second memory comprises one or more cache memory portions, each corresponding to corresponding one of said one or more processors.

5. A receiver comprising:

a waveform receiving input receiving one or more of a plurality of waveforms;
5 an rf down-converter coupled to said waveform receiving input and operable over a plurality of waveforms to produce received digital output information;
an output; and

one or more processors disposed between said output and said rf down-converter and operable in accordance with a plurality of predetermined waveform
10 software each said waveform software being associated with a corresponding one waveform of a plurality of waveforms such that said received digital information is processed in accordance with selected ones of said plurality of predetermined waveform software to produce received digital output information at said output.

15 6. A receiver in accordance with claim 5, comprising:

a first memory having stored therein said plurality of predetermined waveform software;

a second memory for receiving one or more waveform software of said plurality of waveform software for a corresponding number of selected ones of said
20 plurality of waveforms, said second memory receiving said one or more waveform software from said first memory; and

said second memory being coupled to said one or more processors to provide said selected ones of said predetermined waveform software to said one or more processors.

25

7. A receiver in accordance with claim 6, wherein:

said one or more processors are operable to generate a plurality of said waveforms.

8. A method of transmitting information comprising the steps of:
receiving input digital information;

automatically selecting one or more predetermined waveform software from a plurality of waveform software, each waveform software being associated with a

5 corresponding one of a plurality of waveforms;

processing said digital input information by one or more processes in accordance with said selected ones of said plurality of predetermined waveform software to produce digital output information representative of said input digital information; and

10 processing said digital output information with an rf up-converter.

9. A method in accordance with claim 8, comprising:

storing in a first memory said plurality of predetermined waveform software;

retrieving selected ones of said plurality of predetermined waveform software

15 from said first memory;




storing in a second memory said selected ones of said plurality of waveform software for a corresponding number of selected waveforms; and

providing said selected ones of said predetermined waveform software to one or more processors.

20

10. A method in accordance with claim 9, comprising:

operating said one or more processors to generate a plurality of said waveforms.



2/6




FIG. 4

3/6




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11

INTERNATIONAL SEARCH REPORT

Internat. Appl. No.

PCT/US 99/11734

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 H04B1/40

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
IPC 6 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X A	WO 98 14023 A (ADVANCED MICRO DEVICES INC) 2 April 1998 (1998-04-02) abstract page 4, line 1 - page 6, line 13 page 8, line 16 - page 11, line 21 page 14, line 21 - page 15, line 15 figure 3	1-3,5,6, 8,9 4,7,10
X A	EP 0 712 213 A (MOTOROLA INC) 15 May 1996 (1996-05-15) abstract column 5, line 10 - column 10, line 46 figure 1 figure 2	1,2 2,6-10
A	EP 0 782 358 A (LUCENT TECHNOLOGIES INC) 2 July 1997 (1997-07-02) the whole document	1-3,5-9

☐ Further documents are listed in the continuation of box C.



Patent family members are listed in annex.

* Special categories of cited documents:

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search

17 August 1999

Date of mailing of the international search report

24/08/1999

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Lindhardt, U

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No.

PCT/US 99/11734

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 9814023 A	02-04-1998	US 5790817 A EP 0928550 A	04-08-1998 14-07-1999
EP 0712213 A	15-05-1996	US 5621800 A JP 8251040 A	15-04-1997 27-09-1996
EP 0782358 A	02-07-1997	JP 9205474 A	05-08-1997